

# Wavecrest Wiring Instructions

**WARNING:** Do not disconnect or loosen any White neutral wires inside circuit breaker panel

For any questions about Wavecrest please call 732-842-8889.

1. Turn power off to the circuit breaker of the lighting circuit the Wavecrest is connecting too.
2. Remove the load wire from the circuit breaker. This wire connects to the Wavecrest terminal marked RED/OUT.
3. Run a white wire from the Wavecrest terminal marked WHITE/NEU to its own neutral buss connection in the circuit breaker panel.
4. Run a wire from the circuit breaker to the Wavecrest terminal marked BLACK/HOT.
5. Connect the ground wire to ground in the circuit breaker panel.
6. Turn circuit breaker back on to energize the lighting circuit.

